


Multi-Region AC Outlet • Setup Guide

Extron products featuring the Multi-Region AC Outlet allow the use of a variety of AC plug types. Before use, read this guide completely and pay attention to all notes and product specifications.

Extron always recommends using localized AC outlet modules specific to each region, if available.



ATTENTION:

- Even if a plug fits the Multi-Region AC Outlet does not necessarily mean the product is suitable for use in that region.
- Products with the Multi-Region AC Outlet have not been certified nor approved by any safety testing agency, as certification standards for multi-region outlets do not exist.
- **Electrical professionals should be consulted prior to installation to ensure this product can be installed in a manner suitable for use in the project. Before use, ensure the device meets regulatory requirements for your region and complies with local safety and electrical codes.**
- Extron is not liable nor responsible for damage or injury as a result of using this product. It is the responsibility of the qualified installer to ensure applicable safety, compatibility, technical requirements, and system limitations have been addressed and have been conveyed to the end users of the product.
- The Multi-Region AC Outlet is intended for use with low amperage devices, like a laptop power supply.
- The Multi-Region AC Outlet only passes power. It does not convert voltage from 240 V to 120 V.
- The Multi-Region AC Outlet does not provide grounding for all plug types. See notes below plug types and use caution with devices that require grounding. Extron recommends using a GFCI (ground fault circuit interrupter, not included).

| Region | India/Nigeria | Chile/Italy | Angola/Austria | Denmark/Greenland | Singapore/UK/Middle East | Switzerland | Israel |
|-----------|---------------|-------------|----------------|-------------------|--------------------------|----------------------------------|----------------------------------|
| Plug Type | Type D | Type L | Type C | Type K | Type G | Type J | Type H |
| | | | | | | | |
| Note | Plug fits. | Plug fits. | Plug fits. | Plug fits. | Plug fits. | Plug fits. Polarity is reversed. | Plug fits. Polarity is reversed. |

| Region | North America | Germany/Sweden/Egypt | France/Tunisia | Australia/China | South Africa | Brazil |
|-----------|--|---|--|---|---|---|
| Plug Type | Types A & B | Type F | Type E | Type I | Type M | Type N |
| | | | | | | |
| Note | Plug fits. Polarity is reversed. Check for correct voltage before plugging in. | Plug fits. Multi-Region AC Outlet does not have grounding pins for this type. | Plug fits. Multi-Region AC Outlet does not have grounding pin for this type. | Plug does not fit Multi-Region AC Outlet. | Plug does not fit Multi-Region AC Outlet. | Plug does not fit Multi-Region AC Outlet. |